

**APPLICATION FOR  
UNITED STATES LETTERS PATENT**

5           Be it known that we, Dennis Brandon, a citizen of the United States, residing  
at 5114 Woodland Hills Drive, Brentwood, TN, 37027; and Allan Flack, a citizen of the  
United States, residing at 20203 Crowne Brook Circle, Franklin, TN, 37067; have  
invented a new and useful "Electric Generator and Motor Drive System."

**BACKGROUND OF THE INVENTION**

10           This invention relates to the manner of generating, controlling, and  
distributing electrical power from an electrical generator driven by an internal  
combustion engine. The generated electrical power is used to power computer-  
controlled electric motors used as the traction drive in multipurpose lightweight  
15           mowers, and to provide power to on-board mower attachments and external electrical  
equipment.

20           Lightweight mowers exist today in numerous configurations and are  
purposefully built to meet the application needs related to the industry in which they  
are used. Typical examples of these mowers are: Ride on Lawn Mowers; Yard and  
Garden Tractors; Snow Blowers; Golf Carts and Utility Carts; Traffic/Parking Police  
Scooters; Postal Delivery Vehicles; Airport People Movers; Airport Tarmac Shuttle  
Vehicles; Disabled-Person Movers; Hybrid Electric Vehicles; Go-carts; and All-Terrain

Vehicles. These vehicles require a power source that is typically directly or indirectly mechanically linked to the drive wheels for traction and some vehicles are provided with a mechanical connection for powering onboard attachments and externally attached devices. Drive power trains typically have used drive axles, chain/sprocket drives, manual gear-selection transmissions, hydrostatic transmissions, differential  
5 gears, etc. in varying combinations. Steering and speed control techniques vary between the different types of vehicles. Most of the vehicles use a mechanical differential in the drive train to balance the torque applied to the driven wheels so that the wheels can rotate at different speeds when they are required to make a turn.

The power sources for the listed vehicles have been either battery-powered electric motors or internal combustion motors. Both of these sources have shortcomings when they are used separately in a drive system.

Negative features of battery-powered motor driven vehicles have been the battery charge cycle, battery life, battery weight, space required for the batteries, and replacement costs of batteries. Many tasks cannot be completed without the batteries having to be recharged due to the length of operational time required or due to the batteries not being fully recharged. The charging time required can be excessive. The weight of the batteries adds to the load on the drive and a large space is required on the vehicle for mounting the batteries.

20 The internal combustion engine has features that detract from its use in directly driving a transmission and differential. Low output torque at low speed and decreasing torque beyond an optimum speed somewhere below maximum speed

occurs in this engine. A typical engine will have a range of speeds up to 3300 RPM but torque efficiency will be maximized between 2500 and 2800 RPM. The loss of efficiency increases the thermal dissipation in the engine which causes fatiguing and failure of engine components. At low speeds, excessive vibration of the engine is also a problem. Continual operation of the internal combustion engine at its most efficient speed is desirable, but converting the fixed input speed from the engine to a variable speed output from the transmission is not efficient.

With the advent of solid-state power-switching devices such as MOSFETs (metal oxide semiconductor field effect transistors) and IGBTs (insulated-gate bipolar transistors) and microprocessors, the electronic controls for generators and motors that were very complex and expensive in the past, have become economically practical. Today, the electric generator/motor drive provides the flexibility in control and the ruggedness in assembly needed for a small electric motor-driven vehicle. Thus, an improved innovative small vehicle drive system has been developed with an electric generator driven by an internal combustion engine and an electric motor that provides high output torque up to its base speed. The generator supplies electrical power through a power control module to the motor/gearbox on each driven wheel and may provide external power through 110/120V AC and 12V outlets.

## SUMMARY OF THE INVENTION

The present invention is directed towards a drive system, which integrates an electric generator; one or more electric motors and an electronic control module as a variable speed drive in either single, dual or four-wheeled traction drive configurations for a mower. The generator is mechanically driven by the output shaft of an internal combustion engine to generate the electrical power for energizing the electric motors. A central computer in the electronic control module controls the output voltage of the generator and the speed and torque of each of the motors in the drive system. The speed input signal for the motors can be analog signals that come from sources such as a joystick, a potentiometer mounted on a steering wheel, control panel, foot pedal or remote location or digital signals from a digital device. Position/speed detectors on each motor and the generator send signals back to the central computer for closed-loop control of the generator and of the motors. The generator supplies the DC voltage to the power control board for each motor as commanded by the central computer. The rotor of each motor is connected to a gearbox for speed reduction and increased torque that is applied to the wheel mounted on the output shaft of the gearbox. When the motors are not being driven, the generator may optionally supply DC power to the input of an electrical inverter that has an output to standard electric utility AC outlets that can be used to power auxiliary equipment.

This invention integrates 1) a high-efficiency switched reluctance (SR) electric generator driven by an internal combustion engine, 2) high-efficiency switched

reluctance electric motors, 3) speed reduction gearboxes and 4) a power control module. The battery used for starting the internal combustion engine supplies power to the central computer and low voltage circuitry. The central computer in the power control module controls the generator output by controlling the electrical excitation to the generator from a solid-state generator power control board circuit in the power control module. The generator supplies power to each motor that directly drives a gearbox mounted to each driven wheel. In this drive configuration, the internal combustion engine can be run continually at the speed where it is most efficient.

The SR generator is driven by a pulley on its input shaft that is connected via a v-belt to a pulley on the output shaft of the internal combustion engine. The generator can also be driven directly by mechanically connecting it on the engine output shaft. The mechanical connection to the SR generator is driven by the motor at the speed that provides the highest efficiency in the engine. The electrical output of the generator is controlled by the central computer and a generator circuit in the power control module that supplies the excitation to the generator. The generator has an encoder, such as a Hall sensor or optical sensor, on the rotor that sends a position/speed signal to the power control module that must know the location of the rotor for control of commutation in the generator. The output is monitored by the power control module to determine the level of excitation required in order to maintain the correct output level. The output of the generator is electrically supplied to each of the motor power control boards in the power control module.

An inverter module can optionally be connected to the output of the generator to provide AC power for auxiliary equipment. The filtered DC input power from the generator is chopped by a semiconductor H-bridge. The switching in the H-bridge is controlled by the central computer board. The chopped AC output of the H-bridge passes through a low-pass filter to provide two synchronous 110/120 V AC, 50/60 Hz sinewave outputs that are 180 degrees out of phase. The outputs are combined to provide 120V AC and 240V AC outputs to standard AC outlets. As a safety feature, the inverter output may be inhibited when the mower is moving.

Switched reluctance motors are mounted through gearboxes to the driven wheels. The motor receives electrical control from the central computer and its individual motor circuit in the power control module. The motor also has an encoder, such as a Hall sensor or optical sensor, on the rotor that sends a position/speed signal to the central computer in the power control module where it is processed to determine the speed and position of the rotor. Sensorless systems are also well known in the prior art and may be used with this invention. The output shaft of the motor is mechanically directly connected to the input gear in the gearbox.

The preferred embodiment gearbox contains parallel shaft spur gears to provide a 30:1 speed reduction, although different gearing types and reductions may be used for different embodiments. The output shaft of the gearbox is the drive axle for its driven wheel on the mower. Torque is increased in the drive axle by the gear ratio in the gearbox.

The power control module contains the central computer, a generator circuit for the generator, and an individual motor circuit for each motor in the system. The central computer accepts speed control signals as varying DC voltage levels from a joystick or a potentiometer mounted on a foot pedal, control panel, steering wheel or a remote location. A digital input signal from a digital device such as another computer or an encoder can also be accepted by the computer for speed control. Pulses from a position/speed sensor on the rotor of the generator and each motor are fed back to the central computer board. For the generator, the position data is used by the central computer and generator circuit for control of the commutation of the phase excitation in the stator winding. For each motor, a similar action occurs with the motor circuit and the position data is also used by the motor circuit and central computer for commutation control in the phase outputs. In an outer (speed) control loop, the stream of pulses is used by the central computer to determine the speed of each motor and to compare the motor speed to the speed set point to determine if a speed correction signal is required to increase or decrease the power signal to that motor. In an inner "Torque" (current) control loop, a current signal for each motor is detected and sent back to the central computer where it is compared to a current set point to determine if the current should be increased or decreased to the motor whose current was detected. Each motor in the system is controlled by the appropriate motor circuit in this manner.

In this invention, the drive can operate in a forward direction or a reverse direction. The direction of each motor's rotation is controlled independently of the

other motors in the system. The computer can command a reversal of direction for each wheel through a software generated command or a signal from a reverse/forward switch located on the steering wheel, a control panel, a joystick control, or a remote location. This mode of control allows several different functions to be performed.

5 The drive configuration with its control scheme in this invention performs the functions of a mechanical differential through a torque (current) control algorithm that is embedded in the software for the central computer. The torque (current) control algorithm balances the torque and changes the speeds of the driven wheels so that the mower can make a turn in the same manner that a mechanical differential would allow as defined by the formula:

$$\text{Speed input to differential} = \text{Speed left wheel} + \text{Speed right wheel}$$

The motors under most operational conditions will require power from the generator and power control board but when the mower is traveling down an incline or decelerating, the motors will regenerate energy back through the power control board and the generator into the source, an internal combustion engine, or other means, which will slow down the mower. This regenerative braking is desirable to slow down or stop the mower over a reasonable distance.

20 A two-motor drive is also described with a motor mounted on both the left side and the right side of the generator with a gearbox mounted to the face of each motor opposite the face mounted to the generator. The output shaft of each gearbox is the axle for the wheel on each side of the mower. A metal plate is mounted to the bottom



of the assembly tying the two motors/gearboxes and the generator together to stiffen and make a robust assembly.

In this invention, the drive can be configured as an integral assembly as mentioned above or the generator and motor/gearbox wheel units can be mounted on the mower separately with electrical power harnesses and signal harnesses run separately between the components in the drive system over the mower chassis. A motor circuit controlled by the central computer is required for each motor. One, two, and four-wheel drive configurations can be built in this manner.

### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a schematic view of a four-wheel mower that has a generator driven by an internal combustion engine and a single motor driving a reducer/mechanical differential.

Fig. 2A is a top exploded view of the mechanically combined generator/two-motor drive system that is powered by an internal combustion engine.

Fig. 2B is a side exploded view of the mechanically combined generator/two-motor drive system that is powered by an internal combustion engine.

Fig. 3 is a schematic view of a yard tractor with rear wheel drive that embodies the invention as it is configured in Figure 2A and 2B with the front wheels non-driven and used for steering.

Fig. 4 is a schematic view of a three-wheel mower that embodies the invention in the drive system configured to drive two wheels with the third wheel mounted in a swiveling stirrup attached mechanically to the frame of the mower as a caster.

Fig. 5 is a schematic view of a four-wheel mower that embodies the invention with a motor/gearbox on each of two wheels and two non-driven wheels mounted in swiveling stirrups attached mechanically to the mower frame as casters.

Fig. 6 is a schematic view of a three-wheel mower that embodies the invention with a motor/gearbox mounted on the wheel that is mechanically linked to the operator's steering wheel.

Fig. 7 is a schematic view of the central computer and motor control circuits.

Fig. 8 is a schematic view of the central computer and the generator control circuit.

Fig. 9 is a schematic view of the central computer and inverter circuit.

## DESCRIPTION OF THE PREFERRED EMBODIMENTS

Figure 1 shows a drive system 10 for a four-wheeled mower 12 with conventional steering 14. The drive system 10 includes an electric generator 16 which is driven by an internal combustion engine 18 and a motor 20 mounted to a gearbox 22 and standard mechanical differential 24 which drives the individual axles 26, 28 of the two rear wheels 30, 32. This configuration allows the engine 18 to operate continuously at its most efficient speed and eliminates the need for a transmission.

Advances in electric generators 16 and motors 22 have increased their efficiencies to the 80-90% range and improved their reliability. A comparison of different motors 22 and generators 16 was conducted to determine the best type for this drive system. The types considered were inverter-powered AC induction, brush-less dc and switched reluctance. Criteria for the selection were controllability, efficiency, reliability, input speeds, output torque at all speeds, size, construction, thermal management, noise, maintainability, ruggedness and cost. All types have excellent controllability with state of the art controllers, which are of similar complexity. Controllers for both AC induction motors and brush-less motors have power-switching devices that can be damaged by "shoot-through", high current that results from a short circuit across the power supply when both the high-side switch and the low side switch are on at the same time. "Shoot-through" cannot occur in switching devices of a switched reluctance controller because the phase windings of the motor are always between the switches. Switched reluctance motors produce maximum torque from zero speed to base speed without exceeding thermal limits due to all of the motor heat being dissipated in the stator which is the only part of the motor with coil windings. The lack of any windings on the rotor and the thermal transfer ability of the stator make possible a smaller size motor with simpler construction than the other two types. This simple construction reduces the maintenance costs for this type because only the rotor bearings will require servicing or replacement. The switched reluctance motor is less expensive than brush-less dc motors, which require rare earth magnets on the rotor. Due to the absence of magnets

in the switched reluctance motor, demagnetization of magnets is not a concern as it is in brush-less motors and some other types. The torque ripple in the switched reluctance motor may make it noisier than both of the other two types but in an outdoor application the noise is not objectionable. The switched reluctance generator  
5 does not require a fixed speed as is required by an AC induction generator. The switched reluctance motors and generators were selected to be in this drive system because of their ruggedness due to their simple construction, lower mass for the same horsepower, torque/speed characteristics, good thermal transfer and cost of manufacturing. Other motor types may be used with appropriate changes in the operating and control systems.

The gearbox 22 selected to be mounted on the motor output shaft is a parallel shaft spur gearbox for a 30:1 reduction ratio. Due to tooth deflection as the teeth of the gears mesh, spur gears are noisier than some other types such as planetary gears but in this application the noise is not objectionable. The cost of the selected gearbox  
22 is considerably less costly than other types and is widely used in many applications.

Figures 2A and 2B show exploded views of an alternative embodiment of a drive system 10 that is composed of an electric generator 16 mounted between two electric motors 20, 21 with a gearbox 22 mounted on the output side of each motor 20,  
20 21. Each gearbox output shaft forms the drive axle 26, 28 for a wheel 30, 32 (not shown, see Fig. 3). Although the generator 16 and motors 20, 21 are physically mounted together, their shafts are not connected. The input drive to the generator 16

comes from the output shaft 34 (not shown, see Fig. 3) of an internal combustion engine 18 via a v-belt drive 36 (not shown, see Fig. 3). The output of the generator 16 supplies the electrical power to the motors 20, 21 through the motor circuit 38 (not shown, see Fig. 7) for each motor 20, 21. The rotor 40 of each motor 20 is the drive shaft for the gearbox 22 mounted on the output side of each motor 20, 21.

The tractor mower 12 in Figure 3 includes the drive system 10 of Figures 2A and 2B to drive the two rear wheels 30, 32. The two non-driven wheels 31, 33 are used for steering. The internal combustion engine 18 can be operated continually at its torque-efficient speed because the speed of the tractor mower 12 will be independently electronically controlled through the generator 16, power control module and the motors 20, 21 driving the two rear wheels 30, 32. The speed is controlled by either an analog or digital signal from a device operated by the mower operator. The device can be an analog potentiometer mounted on a foot pedal, a control panel, steering wheel or other convenient location. A rotary digital encoder 46, sometimes referred to as a digital potentiometer, can be mounted in one of the same locations and supply a digital signal to the speed control input of the central computer 44 in the power control module. The speed does not change suddenly but is ramped up to the speed set by the operator. The speed changes for each of the driven wheels 30, 32 when the tractor mower 12 makes a turn, or when one of the driven wheels 30, 32 loses traction, are made by the torque (current) control algorithm embedded in the central computer 44. The tractor mower 12 can be driven in reverse after the operator has selected the reverse direction with a forward/reverse switch.

The motors 20, 21 in the drive system 10 for the tractor mower 12 in Figure 3 will regenerate electrical energy when the tractor mower 12 attempts to go faster than the set speed down an inclined surface. The regenerated energy will flow from the motors 20, 21 back through their respective motor circuits 38 and the generator 16 to the internal combustion engine 18 which will slow down. Optionally, the regenerated energy can be stored in the tractor battery (not shown) or dissipated in resistors for braking. As shown, the 110/120V AC and 12V DC outlets are optional for this configuration. Mechanical brakes, as well known in the prior art, may be used on any of these embodiments to provide for additional braking capabilities.

In Figure 4, the three-wheel mower 12 uses the drive system 10 to drive the two driven wheels 30, 32 independently. The third wheel 50 located on the opposite end of the mower 12 is mounted as a caster in a swiveling stirrup 52 attached to the mower 12 frame. The speed and steering are controlled through the two motors 20, 21. The two driven wheels 30, 32 can be on either the front or back of the mower 12.

The motors 20, 21 on the two wheels 30, 32 are controlled through the computer and appropriate motor circuit 38 for independent control of the speed, steering and direction. The central computer 44 will receive a speed input from a control 45, such as a joystick, an analog potentiometer or digital encoder mounted on a foot pedal or other location. If a joystick is used, it can also send the steering, speed, and directional input signals to the central computer 44. The use of a speed-control foot pedal requires separate control devices for steering and direction. A rotary digital encoder with quadrature output can provide a steering and speed signal and a

forward/reverse switch can provide a directional signal to the central computer 44. To control the speeds and directions of the wheels 30, 32, the central computer 44 sends command signals separately to a microprocessor-based motor controller circuit 38 for each motor 20, 21. The motor controller circuit 38 on each wheel 30, 32 controls its  
5 respective circuit output to its motor 20, 21 independently of the controller 38 for other motor 20, 21. The wheels 30, 32, in making a turn, can travel at different speeds required to make the turn. One wheel 30, 32 can be driven in reverse as the other wheel 30, 32 is driven forward to make a zero radius turn when the forward speed is zero. The third wheel 50 in the stirrup 52 will swivel to allow the mower 12  
10 to move in the direction determined by the speeds and direction of the driven wheels 30, 32. The differential steering control through a torque (current) control algorithm is not used in this mower 12.

The generator 16 is driven by the internal combustion engine 18 and controlled by the power control module in the central computer 44. The central computer 44  
15 controls the output of the generator 16 through the electrical excitation from the generator circuit 42 for the generator 16.

The mower 12 in Figure 5 is a four-wheel mower 12 similar to the mower 12 in Figure 4. The only difference is the second non-driven wheel 51. The drive system 10 is configured and functions the same way as the three-wheel drive of Figure 4. Both  
20 non-driven wheels 50, 51 swivel in their stirrups 52 to allow the mower 12 to move in the direction determined by the speed and direction of the driven wheels 30, 32.

In Figure 6, a three-wheel mower 12 has only one driven wheel 30. This embodiment of the invention has the internal combustion engine 18 driving the generator 16 as previously described. The motor 20 and gearbox 22 are mounted on the one swiveling wheel 30 that is used for steering the mower 12. The other two wheels 50, 51 are non-driven and follow at the speed and in the direction determined by the driven wheel 30. The speed control signal to the central computer 44 can be supplied by one of the controls 45, including an analog potentiometer or digital encoder mounted on a foot pedal or on another location that is actuated by the mower 12 operator. Steering is accomplished by the steering wheel 46 that is mechanically linked to the driven wheel 30.

Figs. 7 through 9 show the schematic representation of the circuitry for the central computer's 44 connections for analyzing signals and running the basic operation of the motor circuits 38, the generator circuit 42, and the inverter circuit 56. The central computer receives input from the controls 45, represented as a joystick 70, a foot pedal 72, and a forward/reverse switch 74. Generally, the controls provide both forward reverse control 84 and speed control 86 which are fed into an input output interface 82. The input output interface 82 communicates information from the controls 45 to the microprocessor 90 through a control interface signal 92. The Microprocessor may return information to the input output interface 82 through an interface feedback signal 94 which may be used by the input output interface 82 to generate control feedback signals 88. The control feedback signals 88 may provide



feedback to the operator by feedback gauges 76 such as an analog speed indicator 78 or a digital speed indicator 80.

The microprocessor 90 utilizes the control interface signal 92 along with motor speed signals 96 and 97, clock signal 98, brake inhibit signal 102, bus energy feedback 104, and generator speed/position signal 106 to generate the interface feedback signal 94, motor phase angle/current signals 108 and 109, inverter enable signal 110, and the generator phase angle/current signal 112.

Because the operation of each motor 20, 21 is similar once the individual phase angle/current signal 108 and 109 is received, only one motor operation will be described. The motor phase angle/current signal 108, 109 is used by the motor programmable logic control 114, 115 along with the clock signal 98, motor speed/position feedback signal 116, 117, and motor current limit signal 118, 119 to generate the motor driver control signal 120, 121 and motor current command signal 122, 123. The motor driver control signal 120, 121 is used by the motor power switcher 130, 131 to control the power flow from either a motor bootstrap power supply 124, 125 or the bus voltage 126 through the motor current sensor 128, 129 and into the motor 20, 21. A current sensor signal 132, 133 is sent to the current limit detector 134, 135 from the current sensor 128, 129. The motor 20, 21 is connected to the motor encoder 136, 137 to provide the motor speed/position feedback signal 116, 117 to the motor programmable logic control 114, 115.

Fig. 7 shows the schematic representation of the circuitry for each motor 20, 21 and the connections for electrically powering the motor 20, 21 by the output of a motor

circuit 38 connected to the central computer 44. The motor circuit 38 utilizes solid-state power switching devices controlling the electrical drive level for the motor 20, 21. The acceleration of the motor 20, 21 is controlled by ramping up a speed set-point signal that that is a reference for speed regulation. An encoder 47, either Hall sensors  
5 or optical sensors, on the motor 20, 21 output shaft sends back a stream of pulses that is processed by the central computer 44 to determine the motor 20, 21 speed and the rotational position of the rotor 40. The speed signal is algebraically summed with a speed set-point signal with the resultant error signal digitally processed by the central computer 44 which sends a change in the control signal to the motor circuit 38 to increase or decrease the power to the motor 20, 21 until the speed is equal to the speed set-point. The rotational position is used by the central computer 44 to synchronize the switching of the dc voltage to the phase windings on the stator 48 to the angle of rotation of the rotor 40. The synchronization is necessary for the operation of the SR motor 20, 21.

The drive system 10 is capable of different modes of control as programmed in the central computer 44 because each motor 20, 21 is individually controlled. One mode that is implemented in this invention is the electronically simulated function of a mechanical differential.

The drive configuration with its control scheme in this invention performs the  
20 functions of a mechanical differential through a torque (current) control algorithm that is embedded in the software for the central computer. The torque (current) control algorithm balances the torque and changes the speeds of the driven wheels so

that the mower can make a turn in the same manner that a mechanical differential would allow as defined by the formula:

$$\text{Speed input to differential} = \text{Speed left wheel} + \text{Speed right wheel}$$

5

The mechanical differential can be simulated by implementation of a torque (current) control algorithm. The following algorithm is used:

STEP	Action
1.	Measure the current (torque) into the left motor <b>20</b> .
2.	Measure the current (torque) into the right motor <b>21</b> .
3.	Compare the currents into each of the motors <b>20</b> , <b>21</b> . If the currents are equal, go to step # <b>7</b> .
4.	If the current in the left motor <b>20</b> is lower than the current in the right motor <b>21</b> , decrement the current to the right motor <b>21</b> .
5.	If the current in the right motor <b>21</b> is lower than the current in the left motor <b>20</b> , decrement the current to the left motor <b>20</b> .
6.	If the current in the left motor <b>20</b> is lower than the current in the right motor <b>21</b> , equally increment the speed of the left motor <b>20</b> and decrement the speed of the right motor <b>21</b> .
7.	If the current in the left motor <b>20</b> is higher than the current in the right motor <b>21</b> , equally decrement the speed of the left motor <b>20</b> and increment the speed of the right motor <b>21</b> .

8. (If the currents are unequal?) Go back to step # 1.

9. Measure the speed of the left motor 20.

10. Measure the speed of the right motor 21.

11. Average the speeds of the two motor 20, 21 and compare the average

5 speed to the speed set point. If the average speed is equal to the set point, go to step #

12. Otherwise, go back to step # 1.

12. Measure the current into the fastest motor 20, 21.

13. Measure the current into the slowest motor 20, 21.

14. If the currents into the motors 20, 21 are equal, go to step # 17.

15. If the current into the fastest motor 20, 21 is lower than the current into  
the slowest motor 20, 21, go back to step # 4.

16. If the current into the fastest motor 20, 21 is higher than the current  
into the slowest motor 20, 21, equally decrement the speed to the fastest and  
increment the speed to the slowest motor 20, 21. Increment the current to the slowest  
motor 20, 21. Go back to step # 9.

17. Next step in the control program.

A wheel that loses traction will cause its driving motor 20, 21 to need less  
torque and consequently will draw less current from the motor circuit 38. When the  
20 drop in current to the motor 20, 21 is detected, the central computer 44 starts the  
torque control algorithm to reduce the current to both motors 20, 21 to lower the  
torque until both motors 20, 21 have the same torque and the speed of the motor 20,

21 that lost traction is increased and the speed of the other motor 20, 21 is decreased so that the average of the speeds of the two motors 20, 21 always equals the set speed. The software in the central computer 44 will always attempt to keep the torque of each motor 20, 21 equal to the torque of the other motor 20, 21 by keeping the  
5 currents equal. Also, the central computer 44 will control the speeds of the two motors 20, 21 so that the average of the speeds always equals the set speed. When the mower 12 is making a turn, the wheel on the outside of the turn will increase in speed and the inside wheel will decrease in speed so that the average speed is equal to the set speed with the torque to each wheel being equal.

An optional method of controlling the acceleration and deceleration of the mower can be implemented with acceleration/deceleration curve data in a table stored in the central computer. The acceleration of the mower will follow the curve programmed into the table to the set speed in a predetermined amount of time. Any change in running speed, increase or decrease, will be controlled by the values in the table. Different rates of change can exist for acceleration and deceleration in the forward direction. The acceleration and deceleration in the reverse direction can also have different rates of change.

The speed of the mower can be reduced as it is being steered into a curve so that the mower does not tip over. The speed is coordinated with a steering signal from  
20 an encoder on the steering wheel or other steering device. All movements of the mower can be made in a safe manner either by limiting the speed of the outer wheel or by the speed being coordinated with the steering signal.

Other speed control modules may be added to improve the safe operation of the mower under different conditions. These conditions include the traveling of the mower at an acute angle to the horizon.

Optionally, other speed and torque controls may be implemented, such as  
5 controlled acceleration and deceleration to match predetermined curves, positive traction, and limited slip differential.

The optional method of controlling the acceleration and deceleration of the mower can be implemented with a control table stored in the on-board memory of the microprocessor in the central computer. The acceleration of the mower will follow the curve programmed into the table to the set speed in a predetermined amount of time. The maximum time will occur when the mower is going from a standstill to maximum speed. Any change in running speed, increase or decrease, will be controlled by the values in the table. Different rates of change can exist for acceleration and deceleration in the forward direction. The acceleration and deceleration in the reverse direction can also have different rates of change.

This control method can be used to reduce the speed of the mower when it is being steered into a curve so that the mower does not tip over as it travels through a sharp turning radius. All movements of the mower can be made in a safe manner either by limiting the speed of the outer wheel or by coordinating the speed with a  
20 steering signal from an encoder on the steering wheel or other device.

Other speed control modules may be added to improve the safe operation of the mower under different operating conditions, e.g., the traveling of the mower at an acute angle to the horizon.

Positive traction can be implemented by simulating a locked differential by keeping the speed of the two wheels equal at all times regardless of the loss of traction by either wheel. This mode can be selected by a switch, located on a control panel or other location on the mower 12, that inputs a signal to the central computer 44 to bypass the torque control algorithm. Also, it can be limited to low speeds by detection of speeds lower than a given speed set-point and then bypassing the torque control algorithm until the speed is increased above the set-point. The locked differential can only be used on wheels that are not involved in the steering of the mower 12.

A second type of implementation called limited-slip differential can be made by allowing a set percentage of difference in torque (current) to occur in step # 3 of the torque control algorithm. The central computer 44 can vary the percentage of slip allowed at different speeds by changing the percentage of difference in torque (current) allowed in step # 3 of the torque (current) control algorithm as the speed is changed.

Further modules for the computer may be desirable to control acceleration limits, deceleration limits, turning speed and other operational factors to provide for a margin of safety during operation of the units. These aspects are well known in the prior art and may be implemented in this control scheme.

As shown in Figure 8, the generator phase angle/current signal 112 is used by the generator programmable logic control 140 along with the clock signal 98, generator speed/position feedback signal 142, and generator current limit signal 144 to generate the generator speed/position signal 106, generator driver control signal 146, generator discharge control signal, 148 and generator current command signal 150. The generator driver control signal 146 is used by the generator power switcher 152 to control the phase output currents 154 from a generator bootstrap power supply 156 through the generator current sensor 158 and into the generator 16 to generate the bus voltage 126. A current sensor signal 160 is sent to the current limit detector 162 from the current sensor 158. The generator 16 is connected to the generator encoder 49 to provide the generator speed/position feedback signal 142 to the generator programmable logic control 140.

The generator programmable logic control 140 generates the discharge control signal 148 for the discharge circuit 164 which discharges power from the generator power switcher 152 into the bus capacitors 166. The bus capacitors 166 are also connected to the battery 168. The bus capacitors 166 supply the bus voltage 126 which is monitored by the bus voltage detector 170 for generating the bus energy feedback signal 104 used by the microprocessor 90.

Fig. 8 shows a schematic representation of how the generator 16 output is regulated through its electrical excitation that comes from the generator circuit 42, which is electronically controlled by the central computer 44. A generator output sense signal from the generator encoder 46 is algebraically summed with an output



set-point signal with the resultant error signal digitally processed by the central computer 44 which sends a change in the control signal to the generator circuit 42 if necessary to increase or decrease the excitation to the generator 16 to correct the generator output level. A generator encoder 46 on the generator rotor sends a stream of pulses back to the central computer 44 where it is processed to determine rotational position of the generator rotor. The rotational position is used by the central computer 44 to synchronize the switching of the DC excitation to the phase windings on the generator stator to the angle of rotation of the generator rotor. The synchronization is necessary for the operation of the switched reluctance generator 16. The output of the generator 16 provides the electrical power to a motor circuit 38 for each motor 20, 21 in the drive system 10.

As shown in Figure 9, the brake inhibit signal 102 is generated by a brake switch 63 located on the motor chassis. The brake inhibit signal 102 is used by the microprocessor to control the inverter enable signal 110 which is input into the inverter programmable logic control 172. The inverter programmable logic control 172 uses the inverter enable signal 110, the reset clock signal 98, voltage limit signal 174, and inverter current limit signal 176 to generate the inverter driver control signal 178, inverter voltage command signal, 180 and inverter current command signal 182. The inverter driver control signal 178 is used by the H-bridge power switcher 58 to control the chopped inverter voltage 184 from the upper drive voltage 188 from an inverter bootstrap power supply 186 and the inverter bus capacitors 187 through the low pass filter 60 and into the inverter current sensors 190 to generate

the AC Output **192** for the outlets **62**. A current sensor signal **194** is sent to the inverter current limit detector **196** from the inverter current sensor **190**. The current sensor signal **194** is used by the inverter current limit detector **196** to generate the inverter current limit signal **176**. The inverter bus capacitors **187** are connected to the bus voltage **126**. The low pass filter **60** is also connected to provide an inverter voltage feedback signal **198** to the voltage reference detector **200**. The voltage reference detector **200** uses the inverter voltage feedback signal **198** and the voltage command signal **180** to generate the voltage limit signal **174**.

The schematic representation shown in Figure 9 provides an overview of the implementation of the option for converting the output of the generator **16** to commercial AC voltages for powering auxiliary equipment, e.g., weed-eaters and chainsaws. The filtered DC output of the generator **16** is applied to the input inverter circuit **56** where it is chopped by a semiconductor H-bridge **58**. The switching in the H-bridge **58** is controlled by the central computer **44** board. The synchronized switching signals from the central computer **44** drive the control inputs of the H-bridge **58**. The chopped voltage output is passed through a low-pass filter **60** to provide two synchronous 120 VAC, 60 Hz sine wave outputs that are 180 degrees out of phase. Standard AC outlets **62** are connected to these two outputs in combinations to provide 120V AC and 240V AC for external use from the mower **12**. As a safety feature, the inverter outputs **62** are inhibited by a signal from the switch **63** on the mower **12** brake so that the outputs are not available when the brake is off and the mower **12** is moving.

The scope of this invention is defined by the accompanying claims and not necessarily by specific features of the exemplary embodiments that have been described. Thus, although there have been described particular embodiments of the present invention of a new and useful Electric Generator and Motor Drive System, it is not intended that such references be construed as limitations upon the scope of this invention except as set forth in the following claims.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000